

# SelectorPro - User Manuals

Dear customer,  
Thank you for choosing the smart call restrictor "Selector" for fully control your telephone line's outgoing calls.

In order to program the "Selector" to fit your requirements please pick up any regular telephone and follow the instruction.

We wish you great savings and satisfaction.

## Installation

Replace one of the existing telephone socket with Selector.  
ATTN.  
Please wait 30 seconds after connection before plugging the phone to the jack.

## Symbols description



On hook



Off hook



Middle approval tone



Approval tone



Flash/Hook

Function	Description	Action
1 Set allowed numbers	Act for setting up to 60 different numbers or area codes you want to allow to dial.	<Password> 00000* > 2 > ? . . ? # # <img alt="Phone handset icon"/>
2 Set restricted numbers	Act for setting up to 60 different numbers or area codes you want to restrict to dial.	<Password> 00000* > 1 > ? . . ? # # <img alt="Phone handset icon"/>
3 Restrict all numbers	Act for restrict all numbers except the allowed on section 1	<Password> 00000* > 33 <img alt="Phone handset icon"/>
4 Change password	Default password is 0000, it is recommended to replace with any 4 digits - and remember it.	<Password> 00000* > 5 > ? ? ? ? # # <img alt="Phone handset icon"/>
5 OFF (ON by default)	This action is to turn the selector OFF, all the preferences will be saved, but the "Selector" will not work until you'll turn it ON, as described in the next section.	<Password> 00000* > 32 <img alt="Phone handset icon"/>
6 ON (ON by default)	This action is to turn the selector ON, after you turned it OFF.	<Password> 00000* > 31 <img alt="Phone handset icon"/>
7 Temporary OFF	User can turn OFF the "Selector" for 30 seconds, and it will automatically turn ON.	<Password> 00000# > F  You may dial any number after receiving dial tone.
8 Delete specific number from the memory	User can erase a specific number that was set by sections 1+2	<Password> 00000* > 61 > ? . . ? # # <img alt="Phone handset icon"/>
9 Reset	Completely erasing the memory, clock configuration and password. Returning the Selector to its defaults.	<Password> 00000* > 62 <img alt="Phone handset icon"/> Approval tone will produced after 10 seconds.
10 Speed Dial Configuration	Configure up to 10 fast memory dial. User can dial ?# and flash, and the selector will dial for him. The booths are 1#, 2#, 3#, 4#, 5#, 6#, 7#, 8#, 9#, 0#.	<Password> 00000* > 4 > ? * > ? . . ? # # <img alt="Phone handset icon"/> In order to change number in booth - set the new number to the existing booth.
11 Speed Dial	Act for dial to the configured number to booth from any extension.	? # <img alt="Phone handset icon"/> F After pressing the FLASH button, the selector will dial the number you configured to that booth
12 Clock Setting	User should setup his current time to the selector just if he wants to use automatically programs switches. This clock use 24 hours format. (7:00PM = 19:00)	<Password> 00000* > 74 > ? ? . ? ? # # <img alt="Phone handset icon"/>
13 Chosen hours configuration	Act for choose the time the Selector will automatically work as the chosen program (see next sections)	<Password> 00000* > 71 > ? ? . ? ? * ? ? . ? ? # #
14 Auto Program 1	Set program 1- All numbers will be restricted except the allowed by section 1, in the chosen hours. At the left time the Selector will act as programmed.	<Password> 00000* > 72 <img alt="Phone handset icon"/>
15 Auto Program 2	Set program 2- All numbers will be allowed in the chosen hours. At the left time the Selector will act as programmed.	<Password> 00000* > 73 <img alt="Phone handset icon"/>